


# infinite 3 standard run length

Luminaires may be configured by specifying actual run lengths as shown.

Example: 17' - 9-11/16" run = two 8' and one 4'



run length actual	lamp configuration			run length actual	lamp configuration		
	all 3' lamps	all 4' lamps	3' & 4' lamps		all 3' lamps	all 4' lamps	3' & 4' lamps
2' - 11-1/4"	3			25' - 4-5/8"	6 6 6 6 6		
3' - 11-1/16"		4		26' - 3-7/16"			8 8 8 6
5' - 4-3/4"	6			27' - 10-5/8"	6 6 6 6 6 3		
6' - 4-9/16"			4 3	28' - 3"		8 8 8 8	
7' - 4-3/8"		8		28' - 10-7/16"			6 6 6 6 6 4
7' - 10-3/4"	6 3			30' - 4-5/8"	6 6 6 6 6 6		
8' - 10-9/16"			6 4	30' - 9"			8 8 8 8 3
9' - 10-5/16"			8 3	31' - 8-3/4"		8 8 8 8 4	
10' - 4-3/4"	6 6			32' - 10-9/16"	6 6 6 6 6 6 3		
10' - 10-1/8"		8 4		33' - 2-15/16"			8 8 8 8 6
12' - 4-5/16"			8 6	33' - 10-3/8"			6 6 6 6 6 6 4
12' - 10-11/16"	6 6 3			35' - 2-9/16"		8 8 8 8 8	
13' - 10-1/2"			6 6 4	35' - 4-9/16"	6 6 6 6 6 6 6		
14' - 3-7/8"		8 8		37' - 8-1/2"			8 8 8 8 8 3
14' - 10-5/16"			8 6 3	37' - 10-9/16"	6 6 6 6 6 6 6 3		
15' - 4-11/16"	6 6 6			38' - 8-5/16"		8 8 8 8 8 4	
15' - 10-1/8"			8 6 4	38' - 10-3/8"			6 6 6 6 6 6 6 4
16' - 9-7/8"			8 8 3	40' - 2-1/2"			8 8 8 8 8 6
17' - 4-1/4"			8 6 6	40' - 4-9/16"	6 6 6 6 6 6 6 6		
17' - 9-11/16"		8 8 4		42' - 2-1/8"		8 8 8 8 8 8	
17' - 10-11/16"	6 6 6 3			42' - 10-1/2"	6 6 6 6 6 6 6 6 3		
18' - 10-1/2"			6 6 6 4	44' - 8-1/16"			8 8 8 8 8 8 8 8 3
19' - 3-7/8"			8 8 6	45' - 4-1/2"	6 6 6 6 6 6 6 6 6		
20' - 4-11/16"	6 6 6 6			45' - 7-7/8"		8 8 8 8 8 8 4	
21' - 3-7/16"		8 8 8		47' - 2-1/16"			8 8 8 8 8 8 6
22' - 10-5/8"	6 6 6 6 3			47' - 10-1/2"	6 6 6 6 6 6 6 6 6 3		
23' - 9-7/16"			8 8 8 3	48' - 10-5/16"			6 6 6 6 6 6 6 6 4
23' - 10-7/16"			6 6 6 6 4	49' - 1-5/8"		8 8 8 8 8 8 8	
24' - 9-1/4"		8 8 8 4					

3' & 4' lamps may appear to be different colors when combined in the same run. Consult lamp manufacturer for details.